

# REVAMP1680

PROFESSIONAL  
16-CHANNEL DIGITAL  
POWER AMPLIFIER



REVAMP1680 is a professional 16-channel digital power amplifier with 16 x 80 watts output power @ 4 ohms, but the unit is also bridgeable to 8 x 160 watts @ 8 ohms. This 3 rack units high amplifier with very high channel separation also has a dual analog power supply with toroidal power transformers. The standby power consumption is very low, less than 0.5 watts!

Another smart feature of the REVAMP1680 is the switching mode standby power supply with multiple auto power on/off options. You can power on or power off the unit via a trigger input, audio sense... The trigger input is ideal when you want to switch on the power amplifier automatically using an external AC or DC trigger signal coming from your audio or control system. The amplifier will be switched on as long as the trigger

voltage is present. Alternatively, you can set the power on mode switch to the audio trig position: the amp will automatically switch on when a sufficiently strong audio signal is present at the input and automatically switch off after several minutes of silence.

This amplifier is equipped with 2 stereo bus inputs with pass through. These bus inputs are ideal when you want to hear the same audio signal in different output zones with the advantages you need less audio cables and the installation can be done very fast. With its very low standby consumption and the fact the amplifier can easily be integrated in any audio project, the REVAMP1680 will soon become your favourite multi channel power amplifier.

## TECHNICAL SPECIFICATIONS

depth (incl front) (mm)	421	output power RMS bridged (watts)	8 x 160
19" (483mm wide) rack mounting	Yes	music program power (watts)	16 x 100
height- rack units (1U=44mm) (U)	3	minimum impedance load (ohms)	4
depth (build in) (mm)	405	output channels	16
power supply (volts)	115 - 230 VAC	line input unbalanced	20
power consumption (max) (watts)	1350	frequency response (in Hz)	20 - 30K
output power RMS 4 ohms (watts)	16 x 80	cooling system	convection
output power RMS 8 ohms (watts)	16 x 40		