

# LD-NET 16-E

B05033

## DESCRIPTION

DMX interface 1024ch & 16 Artnet universes

## FEATURES

- This controller is ideal for more demanding projects when a high number of DMX channels are needed and/or when all the fixtures use the ARTNET protocol and has an IP-Ethernet cable wiring.
- 1024 Channel DMX interface when connected to PC.
- 512 Channels in Stand Alone (200KB internal memory = 200 to 2000 DMX steps).
- Up to 16 Artnet universes (8.192 DMX channels) per connected box to the PC when using the LED PLAYER or PRO DMX software. The Artnet will be sent over the RJ45 network connector of your PC.
- Up to 64 Artnet universes (32.768 DMX channels) per connected box to the PC when using the PIXEMM software !
- 4 Dry Contacts on 3~5V (On, On/Off, Release, Restart, Scene Priority).
- Infrared receiver (with optional IR remote).
- 10 scene selections, scene speed, general dimmer and next scene.
- 1 NEXT button for scene selection.
- 24 Hour Timeline for synchronized Lighting, audio and video loops ! (Pro DMX software).
- Works with the Chromateq Led Player, Pro DMX and the Pixxem software (included).
- 3-pin XLR connectors.
- Power supply for the use in standalone mode: 9V to 36V via DC connectors.
- An optional external infra-red receiver can be connected to the unit (LD-512Kit-IR = IR receiver + 2 remote controllers).
- For more information about the software: [www.chromateq.com](http://www.chromateq.com)



[www.briteq-lighting.com](http://www.briteq-lighting.com) | <https://www.facebook.com/Briteq>

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2022 by BEGLEC NV. All rights reserved.



## TECHNICAL SPECIFICATIONS

<b>General : Dimensions (cm)</b>	7 x 9 x 5
<b>General : Weight (kg)</b>	0.5
<b>General : Energy Label</b>	No
<b>General : Color</b>	black
<b>General : Display</b>	none
<b>General : IP rating</b>	indoor
<b>Control : Protocol</b>	Art-Net, DMX
<b>Control : programmable</b>	Yes
<b>Control : upgradable software</b>	Yes
<b>Control : maximum DMX channels</b>	8192
<b>Connections : input</b>	3 pin XLR, usb, RJ45
<b>Connections : output</b>	3 pin XLR
<b>Brand</b>	BRITEQ
<b>EANCode</b>	5420025650335

## YOUR DEALER



[www.briteq-lighting.com](http://www.briteq-lighting.com) | <https://www.facebook.com/Briteq>

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2022 by BEGLEC NV. All rights reserved.