

## CLD1 Compact Loop Driver

The CLD1 Compact Loop Driver is designed for counter systems and small area perimeter loop systems. Measuring only 128 x 74 x 35mm and with an output current of 2.4A RMS, the CLD1 is the smallest and highest performance amplifier in it's class. Designed and built to Ampetronic's high standards of reliability, and backed with a 5 year warranty and Ampetronic support, the CLD1 offers certainty of performance and the lowest lifetime cost available.

Audio quality is ensured with metal loss correction (MLC) combined with Ampetronic's usual high standards of design. The CLD1 is designed for flexibility and convenience, featuring 2 separate microphone inputs with independent level controls, one of which can be configured as a line input. All cable connections are made on a single face of the unit, adding flexibility and further simplifying installation.



### Features

- **Low lifetime cost**
- **5 Year warranty**
- **Very compact**
- **Choice of microphone and pre-formed loop in counter kit**
- **2 independent inputs**
- **1 mic input and 1 switchable mic/line input**
- **Metal loss compensation**
- **All connections to a single face for installation convenience**
- **12V DC or external AC power pack supplied as standard. CLD1-AC has integral power supply**
- **Free technical support**

### Applications include:

- **Ticket and service counters**
- **Retail counters**
- **Information kiosks**
- **Reception desks**
- **Interview rooms**
- **Small meeting rooms**
- **Taxis and private cars**

#### Counter Loops

When supplied as a counter loop kit, the CLD1 comes with choice of microphone, a multi-turn preformed loop power supply and simple installation instructions.

The loop should be mounted vertically in accordance with the installation instructions. Other installation methods are also available.

The CLD1 in this application will project a field to the requirements of IEC60118-4 approximately 1m from the preformed loop.

#### Perimeter Loops – Area Coverage (maximum)

The CLD1 is designed for small perimeter loop applications in rooms or in vehicles. Coverage with a single turn loop:

Room aspect ratio	1:1	2:1	3:1
Maximum area coverage m <sup>2</sup>	20	30	35

- the loop is 1-2m above or below the receiver height
- there are no metal structures in the plane of the loop
- there is sufficient voltage to drive the cable length – check table below.

The CLD1 is DC powered making it ideal for use in small vehicles such as taxis, private cars and small boats. We recommend a multi-turn loop in the headlining of the vehicle cabin – contact Ampetronic for an application guide.

#### Maximum Cable Length

With maximum current output the CLD1 can drive:

- Loops with DC resistance from 0.3 to 1.0Ω
- Impedance up to a maximum of 1.3Ω

When operating below maximum output, the CLD1 can drive longer cable lengths – contact Ampetronic for more details.

Maximum cable length is dependent on cable type and on the application.

Cable type	Maximum Cable Length (m)
0.75mm <sup>2</sup> copper	44
1.0mm <sup>2</sup> copper	57
1.5mm <sup>2</sup> copper	71
1.8mm <sup>2</sup> flat copper tape	101

# CLD1 Product Information

## Ordering Information

The CLD1 compact loop driver can be ordered as a stand alone loop driver or as part of a kit for a specific application.

Counter loop kits comprise 1 x CLD1, 1 x preformed loop, 1 x microphone (choice), 1 x loop present sign, 1 x installation guide and 1 x power supply (region specific). The CLD1 is also available with an integral 240V power supply, part number CLD1-AC.

## Product Description

**Compact loop driver**

## Product Code

**CLD1**

**Counter loop kit + boundary microphone**

**CLD1/CB**

**Counter loop kit + tie clip microphone**

**CLD1/CT**

**Counter loop kit + desktop microphone**

**CLD1/CD**

## Input adaptors and preamplifiers

By using the appropriate adaptor or preamplifier, the CLD1 can be used with inputs from other sources:

### Input type

### Adaptor required

Balanced dynamic mic (XLR)

**MAT60**

Balanced capacitor phantom Power mic (XLR)

**MAT60DC + PSU**

Balanced line level Transformer isolated

**ATT100-T40**

70V / 100V line input Transformer isolated

**ATT100-T70**

Low impedance speaker line, Transformer isolated

**ATT100-T60**

## Standards compliance

The CLD1 is CE marked to all relevant safety and EMC standards

The CLD1 will meet the requirements of IEC60118-4 and the relevant recommendations of BS7594 if specified and installed according to Ampetronic's instructions

## INPUTS

<b>Power</b>	12V DC @ 1.0A max. Fuse fitted to PCB, type T 1.6A L Green LED Power indicator.
<b>AC Power adapter</b>	Input 230V AC 45 – 65 Hz. 110V AC option also available Integral power version also available part number CLD1-AC
<b>Input 1</b>	Microphone input unbalanced electret microphone 3.5mm mono jack socket. Input impedance 8k $\Omega$ . Phantom voltage 6V via 10k $\Omega$ source. Sensitivity -60 dBu for max output Overload level -14 dBu. Recessed control on front panel
<b>Input 2</b>	Switchable line / microphone Recessed switch on connector panel Microphone as for input 1 Line input: Input impedance 820k $\Omega$ Sensitivity -20dBu for max output Overload: >+20dBu.

## OUTPUTS

<b>Drive voltage</b>	>3.2Vrms >4.5V peak at maximum output current
<b>Drive current</b>	<ul style="list-style-type: none"><li>• 2.4 Arms 3.4A peak continuous 1kHz sinewave</li><li>• Short term peak &gt; 4.8A peak</li><li>• LED indicator on front panel</li></ul>
<b>Loop resistance:</b>	0.3 $\Omega$ to 1.0 $\Omega$ resistive or <1.3 $\Omega$ maximum reactive impedance
<b>Loop connector</b>	Vibration proof clamps, accept 0.5 to 1.3mm <sup>2</sup>

## AUDIO SYSTEM

<b>Frequency response</b>	80Hz to 6.3kHz $\pm$ 1.5dB
<b>Automatic gain control</b>	AGC optimised for speech Dynamic range >36dB Green LED indicator on front panel
<b>Metal loss correction</b>	0 to 4.5dB/octave. Recessed control on front panel

## PHYSICAL

<b>Cooling</b>	Natural convection
<b>Dimensions</b>	128mm, 74mm, 35mm
<b>Environment</b>	IP20 : 20 to 90% relative humidity, -20°C to 50°C
<b>Mounting</b>	Horizontal or vertical panel or wall mount, with 2 screw fixings

Boundary Microphone  
Q400



Tie clip Microphone  
EM-1.2



Desktop Microphone  
EM195A



# AMPETRONIC



Issue no 35601-3

[www.ampetronic.com](http://www.ampetronic.com)  
[sales@ampetronic.com](mailto:sales@ampetronic.com)  
[support@ampetronic.com](mailto:support@ampetronic.com)  
phone +44 (0)1636 610062  
fax +44 (0)1636 610063

Northern Road, Newark NG24 2ET. United Kingdom

DISTRIBUTOR