LIVERACK-10

DESCRIPTION

Multi-purpose PA mixer in a handy 19" Rack format, 10 inputs on 7 channels

FEATURES

- Multi-purpose PA mixer in a handy 19" Rack format.
- 10 inputs on 7 channels (4 mic/line, 2 mic/stereo line, 1 player/stereo in/usb).
- The USB connector is Bidirectional (for mono recording or stereo playback via PC/Mac).
- Internal WMA, WAV, FLAC, APE and MP3 media player for USB memory sticks.
- The media player can also be used as a mono mp3 recorder (128kbps).
- Integrated Bluetooth receiver.
- Internal 32bit DSP-effect unit with 16 effects + separate parameter control
- Input control on all the channels:
 - Gain (not on input 9-10/media player)
 - Pan
 - Low Cut switch (not on input 9-10/media player)
 - Treble, mid, bass (Treble, bass on input 9-10/media player)
 - Aux send (Post Fader)
 - Effect send
 - Channel level
 - PFL button (not on input 9-10/media player)
- General 48V Phantom Power switch.
- 1 Master + 1 Group output with individual level control.
- Aux Send output + Return input with individual level control.
- Headphones + control room outputs with level control.







TECHNICAL SPECIFICATIONS

General : Dimensions (cm) $48(W) \times 20(D) \times 15(H)$

General: Weight (kg) 4.14

General: Powerinput AC 100 - 240V, 50/60Hz

General : Energy Label No
General : Power consumption W 25
General : Color black
General : Display No

General: Fixation 19" rack mountable

General: RU No Audio: min. frequency (Hz) 20 Audio: max. frequency (Hz) 20000

Audio : supported audio formats APE, FLAC, MP3, WAV, WMA

Audio: supported audio media USB

Audio: functions equalizer, sound effects
3 pin XLR, rca, jack, usb,

bluetooth

Connections : output3 pin XLR, rca, jackBrandJB SYSTEMSEANCode5420025684057







