



Visit product page



IWM-H

L005776

Beltpack transmitter for the IWM systems with Uni-Directional Headset Microphone, freq.range 863-865MHZ, RF power 10mW, LCD display ,IR synch.

TECHNICAL DETAILS

Technical Specifications

Transmitter

Frequency Range: 863-865MHz

Transmission Method: FM, Mono

Transmitter Power: 5/10/30/100mW

Frequency Response: 50Hz-17KHz

Total Harmonic Distortion: <0.5% at 1KHz

Deviation: 45KHz

Input impedance: 32ohms

Power Supply: DC12V-18V / 500mA

Headset microphone

Polar Pattern ☒ Uni-Directional

Frequency Response ☒ 20Hz-20KHz

Output Impedance ☒ 680Ω

Max SPL: 100dB ☒ T.H.D ☒ 1% at 1kHz ☒

Sensitivity ☒ -47dB 1V/Pa @ 1KHz

Signal/Noise Ratio: 63dB

Cable Length ☒ 1M

PHOTOS



PRODUCT VIDEO



ACCESSORIES




IWM-200

Double True Diversity UHF
Wireless Microphone syst



IWM-100

True Diversity UHF
Wireless Microphone
system, fre



www.fos-lighting.eu

