

DMX TRAITS

CHANNEL										DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	18 CH	36 CH	41 CH	51 CH	81 CH	126 CH	141 CH		
				1	1	1	1	1	1	000-255	Red 1
				2	2	2	2	2	2	000-255	Green 1
				3	3	3	3	3	3	000-255	Blue 1
				4	4	4	4	4	4	000-255	Red 2
				5	5	5	5	5	5	000-255	Green 2
				6	6	6	6	6	6	000-255	Blue 2
				7	7	7	7	7	7	000-255	Red 3
				8	8	8	8	8	8	000-255	Green 3
				9	9	9	9	9	9	000-255	Blue 3
				10	10	10	10	10	10	000-255	Red 4
				11	11	11	11	11	11	000-255	Green 4
				12	12	12	12	12	12	000-255	Blue 4
				13	13	13	13	13	13	000-255	Red 5
				14	14	14	14	14	14	000-255	Green 5
				15	15	15	15	15	15	000-255	Blue 5
				16	16	16	16	16	16	000-255	Red 6
				17	17	17	17	17	17	000-255	Green 6
				18	18	18	18	18	18	000-255	Blue 6
				19	19	19	19	19	19	000-255	Red 7
				20	20	20	20	20	20	000-255	Green 7
				21	21	21	21	21	21	000-255	Blue 7
				22	22	22	22	22	22	000-255	Red 8
				23	23	23	23	23	23	000-255	Green 8
				24	24	24	24	24	24	000-255	Blue 8
						25	25	25	25	000-255	Red 9
						26	26	26	26	000-255	Green 9
						27	27	27	27	000-255	Blue 9
						28	28	28	28	000-255	Red 10
						29	29	29	29	000-255	Green 10
						30	30	30	30	000-255	Blue 10
							31	31	31	000-255	Red 11
							32	32	32	000-255	Green 11
							33	33	33	000-255	Blue 11
							34	34	34	000-255	Red 12
							35	35	35	000-255	Green 12
							36	36	36	000-255	Blue 12
							37	37	37	000-255	Red 13
							38	38	38	000-255	Green 13
							39	39	39	000-255	Blue 13
							40	40	40	000-255	Red 14

DMX TRAITS

CHANNEL										DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	18 CH	36 CH	41 CH	51 CH	81 CH	126 CH	141 CH		
							41	41	41	000-255	Green 14
							42	42	42	000-255	Blue 14
							43	43	43	000-255	Red 15
							44	44	44	000-255	Green 15
							45	45	45	000-255	Blue 15
							46	46	46	000-255	Red 16
							47	47	47	000-255	Green 16
							48	48	48	000-255	Blue 16
							49	49	49	000-255	Red 17
							50	50	50	000-255	Green 17
							51	51	51	000-255	Blue 17
							52	52	52	000-255	Red 18
							53	53	53	000-255	Green 18
							54	54	54	000-255	Blue 18
							55	55	55	000-255	Red 19
							56	56	56	000-255	Green 19
							57	57	57	000-255	Blue 19
							58	58	58	000-255	Red 20
							59	59	59	000-255	Green 20
							60	60	60	000-255	Blue 20
								61	61	000-255	Red 21
								62	62	000-255	Green 21
								63	63	000-255	Blue 21
								64	64	000-255	Red 22
								65	65	000-255	Green 22
								66	66	000-255	Blue 22
								67	67	000-255	Red 23
								68	68	000-255	Green 23
								69	69	000-255	Blue 23
								70	70	000-255	Red 24
								71	71	000-255	Green 24
								72	72	000-255	Blue 24
								73	73	000-255	Red 25
								74	74	000-255	Green 25
								75	75	000-255	Blue 25
								76	76	000-255	Red 26
								77	77	000-255	Green 26
								78	78	000-255	Blue 26
								79	79	000-255	Red 27
								80	80	000-255	Green 27

DMX TRAITS

CHANNEL										DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	18 CH	36 CH	41 CH	51 CH	81 CH	126 CH	141 CH		
								81	81	000-255	Blue 27
								82	82	000-255	Red 28
								83	83	000-255	Green 28
								84	84	000-255	Blue 28
								85	85	000-255	Red 29
								86	86	000-255	Green 29
								87	87	000-255	Blue 29
								88	88	000-255	Red 30
								89	89	000-255	Green 30
								90	90	000-255	Blue 30
								91	91	000-255	Red 31
								92	92	000-255	Green 31
								93	93	000-255	Blue 31
								94	94	000-255	Red 32
								95	95	000-255	Green 32
								96	96	000-255	Blue 32
								97	97	000-255	Red 33
								98	98	000-255	Green 33
								99	99	000-255	Blue 33
								100	100	000-255	Red 34
								101	101	000-255	Green 34
								102	102	000-255	Blue 34
								103	103	000-255	Red 35
								104	104	000-255	Green 35
								105	105	000-255	Blue 35
								106	106	000-255	Red 36
								107	107	000-255	Green 36
								108	108	000-255	Blue 36
								109	109	000-255	Red 37
								110	110	000-255	Green 37
								111	111	000-255	Blue 37
								112	112	000-255	Red 38
								113	113	000-255	Green 38
								114	114	000-255	Blue 38
								115	115	000-255	Red 39
								116	116	000-255	Green 39
								117	117	000-255	Blue 39
								118	118	000-255	Red 40
								119	119	000-255	Green 40
								120	120	000-255	Blue 40

DMX TRAITS

CHANNEL										DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	18 CH	36 CH	41 CH	51 CH	81 CH	126 CH	141 CH		
1	1	1	1								Outer Red: 0 to 100%
2	2	2	2								Outer Green: 0 to 100%
3	3	3	3								Outer Blue: 0 to 100%
		5	4		25	31	61		121	000-255	Outer Color Macros
			5	25	26	32	62		122	000-255	Outer Dimmer: 0 to 100%
			6	26	27	33	63		123	000-255	Outer Dimmer Fine: 0 to 100%
											Outer Strobe Effect
									124	000-002	Open
									124	003-005	Strobe
		8	7	27	28	34	64		124	006-500	Ramp up
									124	051-100	Ramp down
									124	101-150	Ramp up-down
									124	151-200	Lightning
									124	201-255	Random
		9	8	28	29	35	65		125	000-255	Outer Strobe Rate, Speed: Slow to Fast
		10	9	29	30	36	66		126	000-255	Outer Strobe Duration, Duration Slow to Fast
											Outer Program Macro
									127	000-005	No function
									127	006-015	Macro1
									127	016-025	Macro2
									127	026-035	Macro3
									127	036-045	Macro4
									127	046-055	Macro5
									127	056-065	Macro6
									127	066-075	Macro7
									127	076-085	Macro8
									127	086-095	Macro9
									127	096-105	Macro10
		11	10		31	37	67		127	106-115	Macro11
									127	116-125	Macro12
									127	126-135	Macro13
									127	136-145	Macro14
									127	146-155	Macro15
									127	156-165	Macro16
									127	166-175	Macro17
									127	176-185	Macro18
									127	186-195	Macro19
									127	196-205	Macro20
									127	206-215	Macro21
									127	216-225	Macro22
									127	226-235	Macro23
									127	236-245	Macro24
									127	246-255	Macro25
			11		32	38	68		128	0-255	Outer Program Macro Speed

DMX TRAITS

CHANNEL										DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	18 CH	36 CH	41 CH	51 CH	81 CH	126 CH	141 CH		
						39	69	121	129	000-255	White 1
						40	70	122	130	000-255	White 2
						41	71	123	131	000-255	White 3
						42	72	124	132	000-255	White 4
						43	73	125	133	000-255	White 5
						44	74	126	134	000-255	White 6
4	4	4									Inner White: 0 to 100%
				30	33					000-255	Inner White Group 1
				31	34					000-255	Inner White Group 2
			12	32	35	45	75		135	000-255	Inner Dimmer: 0 to 100%
			13	33	36	46	76		136	000-255	Inner Dimmer Fine: 0 to 100%
											Inner Strobe Effect
										000-002	Open
										003-005	Strobe
			14	34	37	47	77		137	006-050	Ramp up
										051-100	Ramp down
										101-150	Ramp up-down
										151-200	Lightning
										201-255	Random
			15	35	38	48	78		138	000-255	Inner Strobe Rate, Speed: Slow to Fast
			16	36	39	49	79		139	000-255	Inner Strobe Duration, Duration Slow to Fast
											Inner Program Macro
										000-005	No function
										006-033	Macro1
										034-060	Macro2
										061-088	Macro3
			12	17		40	50	80	140	089-116	Macro4
										117-144	Macro5
										145-172	Macro6
										173-200	Macro7
										201-228	Macro8
										229-255	Macro9
			18		41	51	81		141	000-255	Inner Program Macro Speed
		13								000-255	In/Out Program Macro Speed, Slow to Fast
5	5	6								000-255	Dimmer: 0 to 100%
6	6	7								000-255	Dimmer Fine: 0 to 100%
											Strobe Effect
										000-002	Open
										003-005	Strobe
										006-050	Ramp up
										051-100	Ramp down
										101-150	Ramp up-down
										151-200	Lightning
										201-255	Random
	8									000-255	Strobe Rate, Speed: Slow to Fast
	9									000-255	Strobe Duration, Duration: Slow to Fast